



8 Channel power sequence controller



CHARACTERISTIC
 Spirit ST-328E is 8-channel wide range power sequence controller, mainly for audio sequence of complex power equipment. It is ideal for public broadcasting, bar, outdoor performances, school lecture room, multimedia conference hall, multi-function hall, training center, villas, hotels or intelligent Home Furnishing etc.

- Features:**
- Sequencing for ON, Invert-sequencing for OFF.
 - PASS button to turn on all channels simultaneously.

TECHNIQUE INDEX

Model	ST-338S
Panel color	Black
Power requirement (single-phase & 3wires)	AC220-250V, 50-60Hz two phase (L, N, PE line, live line, ground wire)
Max. withstanding output reactive power of single channel or overall channel (Relay in control)	2000VA/6000VA
Output power socket	of universal socket standard that flame retardant ABS material and phosphor copper material can withstand the maximum current of 13A.
Circuit board	30A 277V AC
Output relay contact current	30A 277V AC
Power supply	bulkin switching power supply
Voltage	AC220-250V, 50-60Hz
Switch interval (single-channel)	1 second (default value)
External control switch interface	Yes
Voltage display	Yes
Main cable	3*4 square, a total length of 1.2 meters (power plugs not included)
Product size(L*W*H)	190*185*45mm (non-standard 1U)
Flame retardant package size	450*185*45mm (non-standard 1U)
Flame retardant package	19KG, 530*240*550mm
Gross weight	3.2KG



CHARACTERISTIC
 Spirit ST-338S is 8-channel wide range power sequence controller, mainly for audio sequence of complex power equipment. It is ideal for public broadcasting, mini bar, small outdoor performances, the school lecture room, multimedia conference hall, multi-function hall, training center, villas, hotels and Home Furnishing etc.

- Features:**
- Sequencing for ON, Invert-sequencing for OFF.
 - PASS button to turn on all channels simultaneously.
 - Stack machine
 - External control Interface
 - Voltage indicator



8 Channel power sequence controller



CHARACTERISTIC
 Spirit ST-328E is 8-channel wide range power sequence controller, mainly for audio sequence of complex power equipment. It is ideal for public broadcasting, bar, outdoor performances, school lecture room, multimedia conference hall, multi-function hall, training center, villas, hotels or intelligent Home Furnishing etc.

- Features:**
- Sequencing for ON, Invert-sequencing for OFF.
 - PASS button to turn on all channels simultaneously.

TECHNIQUE INDEX

Model	ST-328E
Panel color	Black
Power requirement (single-phase & 3wires)	AC220-250V, 50-60Hz two phase (L, N, PE line, live line, ground wire)
Max. withstanding output reactive power of single channel or overall channel (Relay in control)	2000VA/6000VA
Output power socket	of universal socket standard that flame retardant ABS material and phosphor copper material can withstand the maximum current of 13A.
Circuit board	30A 277V AC
Output relay contact current	30A 277V AC
Power supply	bulkin switching power supply
Voltage	AC220-250V, 50-60Hz
Switch interval (single-channel)	1 second (default value)
Main cable	3*4 square, a total length of 1.2 meters (power plugs not included)
Product size(L*W*H)	460*240*45mm (non-standard 1U)
Flame retardant package size	450*240*45mm (non-standard 1U)
Flame retardant package	22KG, 535*240*550mm
Gross weight	4.2KG